www.instrumentation.it



INSTRUMENTATION DEVICES SRL Via Acquanera 29, 22100 COMO (Italy) tel. +39.031.525391 - fax +39.031.507984 - info@instrumentation.it

KMT - Kraus Messtechnik GmbH

Gewerbering 9, D-83624 Otterfing, Germany, 2 08024-48737, Fax. 08024-5532 Home Page http://www.kmt-gmbh.com, Email: info@kmt-gmbh.com



MT1-PCM

Digital Radio Telemetry System for Strain Gage Applications on Rotating Shafts

"Gain and Auto Zero setting direct from Receiver Side!"



- Easy to assemble and operate
- Strain gage sensors (>350 Ohm)
- Full- and half bridge configuration
- Excitation fixed 4 Volt DC
- Auto-Zero adjustment Setting receiver side
- Gain: 250-8000 Setting receiver side
- **External shunt calibration**

- Digital transmission via radio telemetry 433, 868MHz
- Powering through Lithium battery, >22h work time
- Distance 1-10 meter (rotating application)
- Up to 4 system can work in different radio freq.
- Signal bandwidth 0...500Hz (-3dB)
- Output +/-10V
- System accuracy <0.2%

General Description

The MT1-PCM single-channel telemetry system offers the easiest handling for the wireless radio transmission of strain gage signals from rotating shafts.

The encoder has dimensions (MT1-PCM-STG) of 62x27x13mm (without connectors) and transmitter (40k-Tx) of 62x27x11mm (without connectors). Each module has a weight of about 30g. The encoder/transmitter parts are simply mounted on the rotating shaft with a special fiber reinforced tape and add steel trip.

Powering of the transmission part is with battery 6-9V, power consumption 70mA. The digital data transfer between transmitter and receiver is realized by radio frequency 433MHz or 868MHz, transmitting power 10mW

Functional Description

The MT1-PCM transmitter transmits a digital radio frequency signal to the receiver. The distance between transmitter and receiver (<u>depends of application</u>) is 1-10 meter. "Not rotating Point to Point application upto 100m at free view"

The receiver unit offers a BNC connector at the front panel with analog outputs \pm 10 V. An LED bar indicator shows the actual level and a successful Auto Zero calibration. Overload is indicated by the last LED's in pos. or neg. direction of the bar graph. These OVL-LED's operate in peak-hold mode and are reset by pressing the overload switch.

Strain gage sensors (>350 Ohm) in full- and half- bridge configuration can be directly connected to the transmitter. The excitation is fixed to 4 Volt DC and the gain is set by the gain switch on the receiver side. An auto-zero (AZ) adjustment is executed by pressing the AZ button on the front side of the receiver. The successful AZ operation is indicated by a yellow LED in the middle of the LED bar indicator. When the AZ completes the LED continuously illuminates. A continued flashing of the yellow LED indicates some error in the AZ electronics. In this case please contact the support of KMT. Additional to the AZ you have the possibility to calibrate the bridge by external shunt (+ and -). The AZ setting is stored in a Flash-RAM and thus is not lost during power-off. Use only shielded sensor cable.



<image/> Image: State of the state	Technical Data - Transmitter			
<image/> Image: The set of the s	O KMT O	MT1-PCM-STG	Full and 1/2 bridge = 250 Obm	
<text></text>	+4V EXC www.kmt-gmbh.com	Excitation:	4 VDC (fixed)	
<text></text>		Gain:	250: 500: 1000: 2000: 4000: 8000	
Sinializit			(select able from receiver side)	
<image/> Gen Autocoro ange Autocoro ange Autocoro ange Autocor	0	Gain table		
<image/>		Gain	Autozero range	
<image/>		500	200%	
<image/>		1000	400%	
Image:		4000	400%	
<image/> <text><text><text><text><text><text><text><text><text><text><text><text></text></text></text></text></text></text></text></text></text></text></text></text>		8000	400%	
Shuri Cal: We admail resistor to positive and negative calibration Shuri Cal: - 500 ft (3 dB) Shuri Cal: - 500 ft (3 dB) Shuri Cal: - 10 b + 50 °C. Shuri Cal: - 40 °C. Weight: - 62 c27.11 mm (without connectors) Shuri Cal: - 40 °C. Weight: - 62 c27.11 mm (without connectors) Buti acceleration: - 40 °C. Weight: - 62 c27.11 mm (without connectors) Buti acceleration: - 10 °C. Weight: - 62 c27.11 mm (without connectors) Buti acceleration: - 10 °C. Weight: - 62 c27.11 mm (without connectors) Subicaccieration: - 10 °C. Subicaccieration: - 10 °C. S				
Analog bandwich: 0.500 Hz (3 dB) Analog bandwich: 10 be 80 °C Scanning rate: 2000 Hz Resolution: 12 bld (ADC) Along bandwich: 12 bld (ADC) Along bandwich: 12 bld (ADC) Along bandwich: 10 be 80 °C Scanning rate: 2000 Hz Resolution: 12 bld (ADC) Along bandwich: 12 bld (ADC) Along bandwich: 10 be 80 °C Scanning rate: 2000 Hz Resolution: 43 MHz or 880 MHz, 10 mW transmitting power Dimensions: MT1 PCM-STG eB2271 1mm (without contectors) Waight: each about 30 gran (without contectors) Operating time with 10 CME vegot 0000 Waight: inductive powering Difference MT1 PCM-STG, 450/GND) Power consumption: inductive powering Difference Scional: United with active powering inductive powering Differen		Shunt Cal:	Via external resistor for positive and negative calibration	
Operating frame: : 0.00 Hz Resolution: : 2000 Hz Wight: : each about 30 gram (without connectors): : Wight: : each about 30 gram (without connectors): : Wight: : each about 30 gram (without connectors): : Wight: : each about 30 gram (without connectors): : Wight: : each about 30 gram (without connectors): : Wight: : each about 30 gram (without connectors): : Wight: : each about 30 gram (without connectors): : Wight: : each about 30 gram (without connectors): : Wight: : each about 30 gram (without connectors): : Wight: : each about 30 gram (without connectors): : Wight: : each about 30 gram (without connectors): : Wight: : each about 30 gram (without connectors): : Wight: : : : : : : : : : : : : : : : : : : :		Analog bandwidth:	0 - 500 Hz (-3 dB)	
Subarting face: 2.000 Hz (ACC) Readulation: 2.000 Hz (ACC) Weight: 2.000 Hz (ACC) <		Operating temperature:	- 10 to + 80 °C	
With the set of the set		Resolution:	2000 HZ	
<image/> HURTY THE CANAGEHURTY THE CANAGE </th <th></th> <th></th> <th>1201 (1120)</th>			1201 (1120)	
Carrier frequency: 4.33MHz or 888MHz, 108W transmitting power Dimensions: MT1-PCM-NTT Weight: and habout 30 gram (without connectors) Weight: and habout 30 gram (without connectors) Weight: and habout 30 gram (without connectors) Weight: up to 3000g (only with inductive power) Operating time MT1-PCM-NT1 Operating time MT1-PCM-NT1 Operating time the ductive power/ng Operating time power the ductive		40k-Tx transmitter:		
Dimensions: M11+PCM-STG = 62x27x11mm (without connectors) Weight: each about 30 gram (without cables) Static acceleration: up to 3000g (n) with inductive powert) Weight: each about 30 gram (without cables) Static acceleration: up to 3000g (n) with inductive powert) Weight: each about 30 gram (without cables) Static acceleration: up to 3000g (n) with inductive powert) (powering ime with R-P2 Lithium 1600mAh battery 22h Operating line with CR-P2 Lithium 1600mAh battery 22h Operating line with CR-P2 Lithium 1600mAh battery 22h MI1+PCM STG 5 5 25, 500; 1000; 2000; 4000; 8000 each about 70, 500, 2000; 4000; 8000 Static acceleration: up to 300 Static able M11+PCM STG 5 5 25, 500; 1000; 2000; 4000; 8000 Static acceleration: up to 300 Static able M11+PCM STG 5 5 25, 500; 1000; 2000; 4000; 8000 Static able M11+PCM STG 5 5 25, 500; 1000; 2000; 4000; 8000 Static able M11+PCM STG 5 5 25, 500; 1000; 2000; 4000; 8000 Static acceleration: up to 300 Static able M11+PCM STG 5 5 25, 500; 1000; 2000; 4000; 8000 Weight: up to 100 + 60 °C S		Carrier frequency:	433MHz or 868MHz, 10mW transmitting power	
Weight: each about 30 gram (without connectors): Weight: each about 30 gram (without colles): State acceleration: wp to 3006 (only with inductive power)): Weight: cache about 30 gram (without colles): State acceleration: wp to 3006 (only with inductive power)): Weight: Constrained only with inductive power): Weight: With CR-P2 Lithlum 1600mAh battery 22h Obvio: Inductive powering With CR-P2 Lithlum 1600mAh battery 22h Obvio: Inductive powering With CR-P2 Lithlum 1600mAh battery 22h Obvio: Inductive powering With CR-P2 Lithlum 1600mAh battery 22h Obvio: Inductive powering With CR-P2 Lithlum 1600mAh battery 22h Obvio: Cole 1000: 2000: 6400: 6400: 6400 With PCM-VOI High level inputs: With CR-P2 Lithlum 1600mAh battery 22h Cole 200: 1000: 2000: 4400: 6400 Weight: 0 500 Hot, 2000 Ho		Dimensions:	MT1-PCM-STG = 62x27x13mm (without connectors)	
Weight: up to 30006 (only with inductive power(); with lifthum battery about 1000 Batic acceleration: up to 30006 (only with inductive power(); with lifthum battery 4.54% Powering: MT1-PCAK-STG By battery 6.54% (powering dink-Tx trough MT1-PCM-STG, +5%/(GND) Powering: Inductive powering Weight: Inductive powering MT1-PCM-VOL Range: Range: 20000 Inductive powering MT1-PCM-VOL Range: 20000 Inductive powering MT1-PCM-VOL Range: 20000 Import Notice 0.500 Hz (3 dB) Operating temperature: 1.00 + 80 °C Scanning rate: 2000 Hz Resolution: 2000 Hz More Notice 2000 Hz Resolution: 400 °C Scanning rate: 2000 Hz Resolution			40k-Tx = 62x27x11mm (without connectors)	
Salad: adceleration: with 10 study with mattery back 1000g Powering: MT1+PCM-STR & By battery 6-9V (provering 40k-Tx trough MT1+PCM-STG, +5V/(SND)) Power consumption: 70mA Operating time with CR-P2 Lithium 1600mAh battery 22h Octional: Inductive powering MT1-PCM-STG, +5V/(SND) Power consumption: Torread Operating time WITH-PCM-STG, 500; 1007; 2007; 4000; 6000; 6000 (select able from receiver side) Cational: Inductive powering MT1-PCM-STG, 500; 1000; 2007; 2007; 4000; 8000 (select able from receiver side) Cational: Inductive powering MT1-PCM-STG, 500; 1000; 2007; 4000; 8000 (select able from receiver side) Cational: Inductive powering Cational: 0.500 Hz (3.08) Operating temperature: 10 to + 80 °C Seconing rate: </th <th></th> <th>Weight:</th> <th>each about 30 gram (without cables)</th>		Weight:	each about 30 gram (without cables)	
Powering: MT1-PCM-STG Stp battery 6-9V (powering dW-TA trough MT1-PCM-STG, +5V/GND) Power consumption: 7.07m A Optional: Inductive powering Image: Inductive powering Image: 250; 500; 1000; 2000; 4000; 8000 (geter able from receiver side) Same: Same: 250; 500; 1000; 2000; 4000; 8000 (geter able from receiver side) Same: Same: 250; 500; 1000; 2000; 4000; 8000 (geter able from receiver side) Same: Same: 250; 500; 1000; 2000; 4000; 8000 (geter able from receiver side) Same: Same: 250; 500; 1000; 2000; 4000; 8000 (geter able from receiver side) Same: Same: 250; 500; 1000; 2000; 4000; 8000 (geter able from receiver side) Same: Same: Same: Main: 250; 500; 1000; 2000; 4000; 8000 (geter able from receiver side) Same: Same: Same: Same: 250; 500; 1000; 2000; 4000;		Static acceleration:	with lithium battery about 1000g	
Dever consumption:Crowering 40k-Tx trough MT1-PCM-STG, +5V/GND)Operating timewith CR-P2 Lithium 1600mAh battery 22hOptional:Inductive poweringImage: Consumption:MT1-PCM-STG, +5V/GNDImage: Consumption:-1/10/10/10/10/10/10/10/10/10/10/10/10/10		Powering:	MT1-PCM-STG By battery 6-9V	
Power consumption: YomA Operating time with CR-P2 Lithium 1600mAh battery 22h Deficinal: Inductive powering Image: Landersteepowering Image: Landersteepow			(powering 40k-Tx trough MT1-PCM-STG, +5V/GND)	
Operating time with CR-P2 Lithium 1600mAh battery 22h Operating time with CR-P2 Lithium 1600mAh battery 22h Operating time Inductive powering Image: Inductive powering Image: 26b:500:1000:2000;4000:8000 (select able from receiver side) Image: 26b:200 Image: 26b:200 Image: 26b:200 Image: 26b:200 Image: 21000 Image: 2100 Image: 2000 Image: 10 to + 80 °C Scanning rate: 2000 Image: 12bit (ADC) Image: 22bit (ADC) Image: 22bit (ADC) Image: 12bit (ADC) Image: 12bit (ADC) Image: 12bit (ADC) Image: 12bit (ADC) Image:		Power consumption:	70mA	
Definal:Inductive poweringImage: Image: Ima		Operating time	with CR-P2 Lithium 1600mAh battery 22h	
WIT-PCM-VOLT High level inputs: ± / 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V. Rage: 250; 500; 1000; 2000; 4000; 8000 Control of the second of the se		Optional:		
MITHORNAWITHORNAWITHORNAVolt <t< th=""><th></th><th>Optional.</th><th>Inductive powering</th></t<>		Optional.	Inductive powering	
NT1-PCM VoltGroup tessImage:250, 500, 200, 400, 200, 200, 200, 200, 200, 2			inductive powering	
Image:Image	O KMT O	MT1-PCM-VOLT		
Sain tableSain table <th></th> <th>MT1-PCM-VOLT High level inputs:</th> <th>+/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250: 500: 1000: 2000: 4000: 8000</th>		MT1-PCM-VOLT High level inputs:	+/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250: 500: 1000: 2000: 4000: 8000	
Import and the system of th	MT1-PCM GND	MT1-PCM-VOLT High level inputs: Range:	+/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side)	
Image: Constraint of the systemImage: Constraint of	MT1-PCM GND	MT1-PCM-VOLT High level inputs: Range: Gain table	+/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side)	
Image: Strain of the strain	IN IN IN + Volt	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range	+/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side)	
Image: style styl	Image: Normalized for the second se	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V	+/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side)	
Image: State Stat	Image: Market with the second secon	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V +/- 5V +/- 5V +/- 2.5V	+/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side) Gain 250 500 1000	
Analog bandwidth: 0 - 500 Hz (-3 dB) Operating temperature: - 10 to + 80 °C Scanning rate: 2000 Hz Resolution: 12bit (ADC) 40k-Tx transmitter: Carrier frequency: 40k-Tx transmitter: Carrier frequency: 40k-Tx transmitter: Carrier frequency: 40k-Tx carrier frequency: 433MHz or 868MHz, 10mW transmitting power Dimensions: MT1-PCM-STG = 62x27x13mm (without connectors) 40k-Tx = 62x27x11mm (without connectors) Weight: each about 30 gram (without cables) Static acceleration: Weight: with 11-PCM-STG By battery 6-9V (powering 40k-Tx trough MT1-PCM-STG, +5V/GND) Power consumption: Power consumption: 70mA Operating time with CR-P2 Lithium 1600mAh battery 22h	IN IN IN +- Volt G G	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V +/- 5V +/- 2.5V +/- 1.25V	+/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side) Gain 250 500 1000 2000	
Analog bandwidth: 0 - 500 Hz (-3 dB) Operating temperature: -10 to + 80 °C Scanning rate: 2000 Hz Resolution: 12bit (ADC) 40k-Tx transmitter: Carrier frequency: 433MHz or 868MHz, 10mW transmitting power Dimensions: MT1-PCM-STG = 62x27x13mm (without connectors) 40k-Tx transmitter: Carrier frequency: 433MHz or 868MHz, 10mW transmitting power Dimensions: MT1-PCM-STG = 62x27x13mm (without connectors) 40k-Tx e 62x27x11mm (without connectors) Weight: each about 30 gram (without cables) Static acceleration: Up to 3000g (only with inductive power!) with lithium battery about 1000g Powering: MT1-PCM-STG By battery 6-9V (powering 40k-Tx trough MT1-PCM-STG, +5V/GND) Power consumption: Power consumption: 70mA Operating time with CR-P2 Lithium 1600mAh battery 22h Detional: Inductive powering	IN IN IN +- Volt Good Good	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V +/- 5V +/- 2.5V +/- 0.625V +/- 0.3125V	+/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side) Gain 250 500 1000 2000 4000 8000	
Operating temperature: - 10 to + 80 °C Scanning rate: 2000 Hz Resolution: 12bit (ADC) 40k-Tx transmitter: Carrier frequency: 40k-Tx transmitter: Carrier frequency: 40k-Tx transmitter: Dimensions: MT1-PCM-STG = 62x27x13mm (without connectors) 40k-Tx = 62x27x11mm (without connectors) 40k-Tx = 62x27x11mm (without connectors) Weight: each about 30 gram (without cables) Static acceleration: up to 3000g (only with inductive power!) with lithium battery about 1000g Powering: MT1-PCM-STG By battery 6-9V (powering 40k-Tx trough MT1-PCM-STG, +5V/GND) Power consumption: 70mA Operating time with CR-P2 Lithium 1600mAh battery 22h Optional: Inductive powering	IN IN IN IN IN +- Volt GO	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V +/- 5V +/- 2.5V +/- 0.625V +/- 0.3125V	+/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side)	
Scanning rate: 2000 Hz Resolution: 12bit (ADC) 40k-Tx transmitter: Carrier frequency: Carrier frequency: 433MHz or 868MHz, 10mW transmitting power Dimensions: MT1-PCM-STG = 62x27x13mm (without connectors) 40k-Tx = 62x27x11mm (without connectors) 40k-Tx = 62x27x11mm (without connectors) Weight: each about 30 gram (without cables) Static acceleration: up to 3000g (only with inductive power!) with lithium battery about 1000g Powering: MT1-PCM-STG By battery 6-9V (powering 40k-Tx trough MT1-PCM-STG, +5V/GND) Power consumption: 70mA Operating time with CR-P2 Lithium 1600mAh battery 22h Dimension: Inductive powering	Image: Constraint of the second se	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V +/- 5V +/- 2.5V +/- 0.625V +/- 0.3125V Analog bandwidth:	+/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side)	
Resolution: 12bit (ADC) 40k-Tx transmitter: Carrier frequency: 40k-Tx = 62x27x13mm (without connectors) 40k-Tx = 62x27x11mm (without connectors) Weight: each about 30 gram (without colles) Static acceleration: up to 3000g (only with inductive power!) with lithium battery about 1000g Powering: Power consumption: 70mA Operating time with CR-P2 Lithium 1600mAh battery 22h Optional: Inductive powering	Image: Constraint of the state of the st	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V +/- 2.5V +/- 0.625V +/- 0.3125V Analog bandwidth: Operating temperature:	+/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side)	
40k-Tx transmitter: Carrier frequency: 433MHz or 868MHz, 10mW transmitting power Dimensions: MT1-PCM-STG = 62x27x13mm (without connectors) 40k-Tx = 62x27x11mm (without connectors) 40k-Tx = 62x27x10mm (without connectors) 40k-Tx = 62x27x10mm (without connectors) 40k-Tx = 62x27x11mm (without connectors) 40k-Tx = 62x27x11mm (without connectors) 40k-Tx = 62x27x10mm	Image: Constraint of the state of the st	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V +/- 5V +/- 2.5V +/- 0.25V +/- 0.3125V Analog bandwidth: Operating temperature: Scanning rate:	+/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side) Gain 250 500 1000 2000 4000 8000 0 - 500 Hz (-3 dB) - 10 to + 80 °C 2000 Hz	
Image: Construction Carrier frequency: 433MHz or 868MHz, 10mW transmitting power Image: Construction MT1-PCM-STG = 62x27x13mm (without connectors) Image: MT1-PCM-STG = 62x27x11mm (without connectors) Image: MT1-PCM-STG = 62x27x11mm (without connectors) Weight: each about 30 gram (without cables) Static acceleration: up to 3000g (only with inductive power!) with lithium battery about 1000g Powering: MT1-PCM-STG By battery 6-9V (powering 40k-Tx trough MT1-PCM-STG, +5V/GND) Power consumption: 70mA Operating time with CR-P2 Lithium 1600mAh battery 22h Optional: Inductive powering		MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V +/- 5V +/- 2.5V +/- 0.625V +/- 0.625V +/- 0.3125V Analog bandwidth: Operating temperature: Scanning rate: Resolution:	+/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side)	
Image: State of the second	<image/>	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V +/- 5V +/- 2.5V +/- 0.625V +/- 0.625V +/- 0.3125V Analog bandwidth: Operating temperature: Scanning rate: Resolution: 40k-Tx transmitter:	+/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side)	
Wight: each about 30 gram (without connectors) Weight: each about 30 gram (without cables) Static acceleration: up to 3000g (only with inductive power!) with lithium battery about 1000g Powering: MT1-PCM-STG By battery 6-9V (powering 40k-Tx trough MT1-PCM-STG, +5V/GND) Power consumption: 70mA Operating time with CR-P2 Lithium 1600mAh battery 22h Optional: Inductive powering	<image/> <image/> <image/> <image/> <image/> <image/> <image/>	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V +/- 5V +/- 2.5V +/- 0.625V +/- 0.3125V Analog bandwidth: Operating temperature: Scanning rate: Resolution: 40k-Tx transmitter: Carrier frequency:	Houcave powering +/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side) Gain 250 500 1000 2000 4000 8000 0 - 500 Hz (-3 dB) - 10 to + 80 °C 2000 Hz 12bit (ADC)	
Weight: each about 30 gram (without cables) Static acceleration: up to 3000g (only with inductive power!) with lithium battery about 1000g Powering: MT1-PCM-STG By battery 6-9V (powering 40k-Tx trough MT1-PCM-STG, +5V/GND) Power consumption: 70mA Operating time with CR-P2 Lithium 1600mAh battery 22h Optional: Inductive powering	<image/>	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V +/- 5V +/- 2.5V +/- 0.625V +/- 0.3125V Analog bandwidth: Operating temperature: Scanning rate: Resolution: 40k-Tx transmitter: Carrier frequency: Dimensions:	Houcave powering +/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side) Gain 250 500 1000 2000 4000 8000 0 - 500 Hz (-3 dB) - 10 to + 80 °C 2000 Hz 12bit (ADC) 433MHz or 868MHz, 10mW transmitting power MT1-PCM-STG = 62x27x13mm (without connectors)	
Static acceleration: up to 3000g (only with inductive power!) with lithium battery about 1000g Powering: MT1-PCM-STG By battery 6-9V (powering 40k-Tx trough MT1-PCM-STG, +5V/GND) Power consumption: 70mA Operating time with CR-P2 Lithium 1600mAh battery 22h Optional: Inductive powering	<image/> <image/> <image/> <image/> <image/>	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V +/- 2.5V +/- 0.625V +/- 0.3125V Analog bandwidth: Operating temperature: Scanning rate: Resolution: 40k-Tx transmitter: Carrier frequency: Dimensions:	+/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side) Gain 250 500 1000 2000 4000 8000 0 - 500 Hz (-3 dB) - 10 to + 80 °C 2000 Hz 12bit (ADC) 433MHz or 868MHz, 10mW transmitting power MT1-PCM-STG = 62x27x13mm (without connectors) 40k-Tx = 62x27x11mm (without connectors)	
Image: MT1-PCM-STG By battery 6-9V (powering 40k-Tx trough MT1-PCM-STG, +5V/GND) Power consumption: 70mA Operating time with CR-P2 Lithium 1600mAh battery 22h Optional: Inductive powering	<image/> <image/>	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V +/- 5V +/- 2.5V +/- 0.625V +/- 0.3125V Analog bandwidth: Operating temperature: Scanning rate: Resolution: 40k-Tx transmitter: Carrier frequency: Dimensions: Weight:	Houcave powering +/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side) Gain 250 500 1000 2000 4000 8000 0 - 500 Hz (-3 dB) - 10 to + 80 °C 2000 Hz 12bit (ADC) 433MHz or 868MHz, 10mW transmitting power MT1-PCM-STG = 62x27x13mm (without connectors) 40k-Tx = 62x27x11mm (without connectors) each about 30 gram (without cables)	
(powering 40k-Tx trough MT1-PCM-STG, +5V/GND) Power consumption: 70mA Operating time with CR-P2 Lithium 1600mAh battery 22h Optional: Inductive powering	<image/> <image/> <image/> <image/>	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V +/- 2.5V +/- 2.5V +/- 0.625V +/- 0.625V +/- 0.3125V Analog bandwidth: Operating temperature: Scanning rate: Resolution: 40k-Tx transmitter: Carrier frequency: Dimensions: Weight: Static acceleration:	+/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side) Gain 250 500 1000 2000 4000 8000 0 - 500 Hz (-3 dB) - 10 to + 80 °C 2000 Hz 12bit (ADC) 433MHz or 868MHz, 10mW transmitting power MT1-PCM-STG = 62x27x13mm (without connectors) 40k-Tx = 62x27x11mm (without connectors) each about 30 gram (without cables) up to 3000g (only with inductive power!) with lithum battory about 1000c	
Power consumption: 70mA Operating time with CR-P2 Lithium 1600mAh battery 22h Optional: Inductive powering	<image/> <image/> <image/> <image/>	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V +/- 5V +/- 2.5V +/- 0.625V +/- 0.625V +/- 0.3125V Analog bandwidth: Operating temperature: Scanning rate: Resolution: 40k-Tx transmitter: Carrier frequency: Dimensions: Weight: Static acceleration: Powering:	#/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side)	
Operating time with CR-P2 Lithium 1600mAh battery 22h Optional: Inductive powering	<image/> <image/> <image/>	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V +/- 5V +/- 2.5V +/- 0.625V +/- 0.3125V Analog bandwidth: Operating temperature: Scanning rate: Resolution: 40k-Tx transmitter: Carrier frequency: Dimensions: Weight: Static acceleration: Powering:	#/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side) Gain 250 500 1000 2000 4000 8000 0 - 500 Hz (-3 dB) - 10 to + 80 °C 2000 Hz 12bit (ADC) 433MHz or 868MHz, 10mW transmitting power MT1-PCM-STG = 62x27x13mm (without connectors) 40k-Tx = 62x27x11mm (without connectors) each about 30 gram (without cables) up to 3000g (only with inductive power!) with lithium battery about 1000g MT1-PCM-STG By battery 6-9V (powering 40k-Tx trough MT1-PCM-STG, +5V/GND)	
Optional: Inductive powering	<image/> <image/> <image/> <image/>	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V +/- 2.5V +/- 1.25V +/- 0.625V +/- 0.3125V Analog bandwidth: Operating temperature: Scanning rate: Resolution: 40k-Tx transmitter: Carrier frequency: Dimensions: Weight: Static acceleration: Powering: Power consumption:	#/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side) Gain 250 500 1000 2000 4000 8000 0 - 500 Hz (-3 dB) - 10 to + 80 °C 2000 Hz 12bit (ADC) 433MHz or 868MHz, 10mW transmitting power MT1-PCM-STG = 62x27x13mm (without connectors) 40k-Tx = 62x27x11mm (without connectors) each about 30 gram (without cables) up to 3000g (only with inductive power!) with lithium battery about 1000g MT1-PCM-STG By battery 6-9V (powering 40k-Tx trough MT1-PCM-STG, +5V/GND) 70mA	
Optional: Inductive powering	<image/> <image/> <image/> <image/> <image/>	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V +/- 5V +/- 2.5V +/- 1.25V +/- 0.625V +/- 0.625V +/- 0.3125V Analog bandwidth: Operating temperature: Scanning rate: Resolution: 40k-Tx transmitter: Carrier frequency: Dimensions: Weight: Static acceleration: Power consumption: Operating time	#/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side)	
	<image/> <image/> <image/> <image/> <image/> <image/>	MT1-PCM-VOLT High level inputs: Range: Gain table INPUT range +/- 10V +/- 5V +/- 2.5V +/- 0.625V +/- 0.3125V Analog bandwidth: Operating temperature: Scanning rate: Resolution: 40k-Tx transmitter: Carrier frequency: Dimensions: Weight: Static acceleration: Powering: Power consumption: Operating time	#/- 10V, 5V, 2.5V, 1.25V, 0.625V or 0.3125V 250; 500; 1000; 2000; 4000; 8000 (select able from receiver side) Gain 250 500 1000 2000 4000 8000 0 - 500 Hz (-3 dB) - 10 to + 80 °C 2000 Hz 12bit (ADC) 433MHz or 868MHz, 10mW transmitting power MT1-PCM-STG = 62x27x13mm (without connectors) 40k-Tx = 62x27x11mm (without connectors) each about 30 gram (without cables) up to 3000g (only with inductive power!) with lithium battery about 1000g MT1-PCM-STG By battery 6-9V (powering 40k-Tx trough MT1-PCM-STG, +5V/GND) 70mA with CR-P2 Lithium 1600mAh battery 22h	



Version 2010-01

4

Technical Data are subject to change without notice!



www.instrumentation.it

INSTRUMENTATION DEVICES SRL

Via Acquanera 29, 22100 COMO (Italy) tel. +39.031.525391 - fax +39.031.507984 - info@instrumentation.it